How to copy and paste a model in ST-Sim

Background

There are more than 1,000 BpS models in the LANDFIRE ST-Sim database. Editing and running an individual BpS model is much more efficient if the BpS record (called a scenario in ST-Sim) is in it's own library. This tutorial demonstrates how to copy and paste an individual or selected BpS into a new ST-Sim library. Here are a few ST-Sim terms that you need to understand for this tutorial.



Open the LANDFIRE library and create a new library

- 1. From the **File** menu select **Open Library**, navigate to the location of your LANDFIRE .sim database and click the **Open** button.
- 2. From the File menu select New Library. Name the new library and save it.

Copy and paste the scenario		SyncroSim File Edit View Model Window F în ♣ ⊒ × ► ★ × ► ≿ Ø	elp	Poten Task Minut Minut	_ D X
1.	Right click on the	Libraries			ŕ
	AllModels	BpSModels	Paste Strata		X
	scenario and Copy		Name 0110080		
	it.		0110180 0110350		
2.	Right click on the		0110360 0110370		
	new library and		0110390 0110411 0110412		
	Paste Strata.		0110420 0110450		E
3.	In the Paste Stata	Active Result Scenarios	0110460 0110531 0110550		
	window, select the	Charts Maps Export	0110600		
	BpS model you		Select All Merge Dependencies	ОК	Cancel

want and click **OK**. To select multiple BpS, hold the down the **Ctrl** key while making your selection and then click **OK**.

Note: The pasted scenario will be given the name "AllModels – Copy" by default, but if you open the Pathways menu you will see that only the selected strata was pasted as shown in the example below. Right click on the project and/or the scenario to access the **Rename** option.

